

# HSP1 Model Number Builder


## High Power Amplifier

### Frequency Band <sup>1</sup>

**U1** = 340.0-399.9 MHz  
**L1** = 1435-1535 MHz  
**L2** = 1700-1850 MHz  
**S1** = 2200-2399 MHz  
**S2** = 2400-2499 MHz  
**S3** = 2200-2499 MHz  
**C1** = 4400-4900 MHz  
**C2** = 4900-4999 MHz  
**C3** = 4400-4999 MHz  
**ZZ** = Custom <sup>2</sup>

### RF Power (Choose 1 to 2 Options)

**2** = Include 2.0 W  
**0** = Do Not Include 2.0 W  
**1** = Include 1.0 W  
**0** = Do Not Include 1.0 W  
**H** = Include 500 mW  
**0** = Do Not Include 500 mW  
**Q** = Include 250 mW  
**0** = Do Not Include 250 mW



### Notes:

1) HSP1 power amplifiers must be matched to the connected transmitters



Advanced Microwave Products  
 8748 Technology Way  
 Reno, NV 89521

Phone: (775) 345-9933  
 Fax: (775) 345-9913  
 E-mail: sales@advmw.com  
 Web: www.advmw.com